

<b>Calendar &amp; Tasks .....</b>	<b>9-2</b>
Calendar .....	9-2
Tasks .....	9-5
<b>Alarms .....</b>	<b>9-7</b>
Using Alarms .....	9-7
<b>Wakeup TV .....</b>	<b>9-9</b>
Using Wakeup TV .....	9-9
<b>Relaxation Time .....</b>	<b>9-11</b>
Playing Animation with Music & Illumination .....	9-11
<b>Calculator .....</b>	<b>9-12</b>
Using Calculator .....	9-12
<b>Expenses Memo .....</b>	<b>9-13</b>
Adding Expenses .....	9-13
<b>Osaifu-Keitai® .....</b>	<b>9-14</b>
Osaifu-Keitai® (Japanese) .....	9-14
Locking IC Card .....	9-15
<b>Simulated Call .....</b>	<b>9-18</b>
Faking Incoming Calls .....	9-18
<b>Stopwatch .....</b>	<b>9-19</b>
Using Stopwatch .....	9-19
<b>Countdown Timer .....</b>	<b>9-20</b>
Using Countdown Timer .....	9-20
<b>World Clock .....</b>	<b>9-21</b>
Opening World Clock .....	9-21

<b>Hour Minder .....</b>	<b>9-22</b>
Using Hour Minder .....	9-22
<b>Pedometer .....</b>	<b>9-23</b>
Using Pedometer .....	9-23
<b>Document Viewer .....</b>	<b>9-25</b>
Opening PC Documents .....	9-25
<b>Notepad .....</b>	<b>9-26</b>
Saving Text .....	9-26
<b>ASCII Art .....</b>	<b>9-27</b>
Using ASCII Art .....	9-27
<b>Voice Recorder .....</b>	<b>9-28</b>
Recording/Playing Voice .....	9-28
<b>Scan Barcode .....</b>	<b>9-29</b>
Scanning Barcodes .....	9-29
<b>Create QR Code .....</b>	<b>9-30</b>
Creating QR Codes .....	9-30
<b>Scan Card .....</b>	<b>9-31</b>
Scanning Business Cards .....	9-31
<b>Scan Text .....</b>	<b>9-32</b>
Scanning Text .....	9-32
<b>Kanji Grabber .....</b>	<b>9-33</b>
Using Kanji Grabber .....	9-33
<b>Additional Functions .....</b>	<b>9-34</b>
<b>Troubleshooting .....</b>	<b>9-46</b>

# 9

## Handy Extras

## Calendar

### Opening Calendar


- 1



Calendar Window

### Toggling View

Press to toggle Calendar window:




Month View



3Month View



6Month View



Week View

### Key Assignments

#### All Views

Open Previous Page	
Open Next Page	
Open Help	

#### Month/3Month View

Select Date	
Go to Current Date	

#### 6Month View

Go to Current Month	
Select Month	

#### Week View

Select Date	
Select Time Block	

### Advanced

-

## Saving Schedules


Follow these steps to save subject, start/end date/time, Alarm and schedule details: (Enter Subject or Description to save entry.)

- 1 In Calendar window, select date** ➔ ●



- 2 <Add New Entry>** ➔ ●

- 3 Enter subject** ➔ ●



- 4 Enter start date/time** ➔ ●



- 5 End:** ➔ ● ➔ Enter end date/time ➔ ●

- 6 Alarm:** ➔ ●

- 7 Alarm Time:** ➔ ● ➔ Select time ➔ ● ➔ ⌚

- 8 Description:** ➔ ● ➔ Enter schedule details ➔ ●

- 9 ⌚ ➔ Saved**

### All-Day Schedule

In 4, ☺ ➔ ● ➔ From 8

### Custom Alarm Time

In 7, Alarm Time: ➔ ● ➔ Other ➔ ● ➔ Enter date/time ➔ ● ➔ ⌚ ➔ From 8

## At Alarm Time

Alarm activates; sounds/vibrates by related settings.



### Stopping Alarm to Return to Standby

- While Alarm sounds/vibrates, press ●, ☎ or ⏸.

### Stopping Alarm to Open Schedule

- While Alarm sounds/vibrates, press a key other than ●, ☎ or ⏸.

### When Another Function is Active

- Alarm may not activate until handset returns to Standby.

### Incoming Calls

- Active Alarm stops for incoming calls. Information window opens after handset returns to Standby.

## Advanced

- Setting Category/Location ● Creating Categories ● Saving repetitive schedules ● Editing entries ● Changing Alarm tone/video & duration ● Changing Alarm volume ● Selecting Vibration option (And more on P.9-35 - 9-36)

## Opening Schedules/Tasks

- 1 In Calendar window, select date ➡



Schedule List

- 2 Select schedule or task ➡
- 3 ➡ Standby returns

## Opening Task List

In 2, select task ➡ ➡ *Go to Tasks* ➡

## Accessing Secret Entries

[Calendar Window] ➡ *Unlock Temporarily* ➡ ➡ *Enter Handset Code* ➡

## Opening Related Message

Open schedule-related messages saved from Messaging message list.

- 1 In schedule list, select schedule ➡
- 2 ➡ *Related Mail* ➡
  - Related message opens.
  - To return to schedule window, press .

## Deleting Message from Schedule

After 1, ➡ *Related Mail:* ➡ ➡ *Yes* ➡ ➡

## Deleting Schedules

## One Entry

- 1 In schedule list, select schedule ➡
  - 2 *Delete* ➡ ➡ *This Appointment* ➡ ➡ *Yes* ➡
- All Entries of the Day
- 1 In Calendar window, select date ➡
  - 2 *Delete* ➡ ➡ *All This Day* ➡ ➡ *Yes* ➡

## Advanced

1

- Searching entries ● Checking memory status ● Deleting all entries ● Deleting entries by specifying week (Week View) ● Deleting entries by specifying month (Month/3Month View) ● Deleting entries in six months (6Month View) (P.9-36)

## Saving Tasks


100

- 1**  ➔ **Tools** ➔  ➔ In PIM/  
Lifestyle menu, **Tasks** ➔ 



- 2 <Add New Entry> ➡ ●

- 3 Enter subject** ➡ 



- 4 Enter due date/time ➡** 



- 5 Alarm:** ➡ 



- 6 Alarm Time:** ➡  ➡ **Select**  
**time** ➡  ➡ 

- 7** **Description:** ➡  ➡ Enter  
task details ➡ 

-   ➡ **Saved**

### Task with No Due Date/Time

In 4,   $\Rightarrow$    $\Rightarrow$  From 7

### Custom Alarm Time

In ⑥, Alarm Time: ➡ ☒ ➡ Other ➡

⊙ ➡ Enter date/time ➡ ⊙ ➡ Ⓜ ➡

From **7**

Advanced

- 
 Hiding tasks 
  Editing tasks 
  Setting priority 
  Changing Alarm tone/video & duration 
  Changing Alarm volume 
  Selecting Vibration option 
  Sounding Alarm tone even in Manner mode (**P.9-36 - 9-37**)

## At Alarm Time

Alarm activates; sounds/vibrates by related settings.



## Stopping Alarm to Return to Standby

- While Alarm sounds/vibrates, press or .

## Stopping Alarm to Open Task

- While Alarm sounds/vibrates, press a key other than , , or .

## When Another Function is Active

- Alarm may not activate until handset returns to Standby.

## Incoming Calls

- Active Alarm stops for incoming calls. Information window opens after handset returns to Standby.

## Opening Tasks

- ➔ **Tools** ➔ ➔ **In PIM/ Lifestyle menu, Tasks** ➔



Task List

- Use to open completed or uncompleted task list.

- Select task ➔



- ➔ **Standby returns**

## Accessing Secret Entries

After , ➔ **Unlock Temporarily** ➔

➔ **Enter Handset Code** ➔

## Marking Tasks as Completed

After , select task ➔

## Deleting Tasks

## One Entry

- In task list, select task ➔

- Delete** ➔

- This Task** ➔ ➔ **Yes** ➔

## All Completed Tasks

- In task list,

- Delete** ➔

- All Comp. Tasks** ➔ ➔ **Yes** ➔

## Advanced

- Searching tasks Sorting tasks by priority Checking memory status Deleting all tasks (P.9-37)

## Setting Alarm

Follow these steps to set Alarm to sound at a specific time on a specific day of the week: (Set Snooze--Alarm repeats at set interval--Alarm Volume and Duration.)

- 
- Alarms
- :--
- :--

**2** --:-- ➡  ➡ Enter hour (24-hour format) ➡ Enter minutes ➡ 



- Repeat
- ☒ Once
  - ☐ Every Day (All)
  - ☐ Selected Days

- 

- 7 Select interval** ➡ ☒ **Other.**

- 13**  ➡ **Alarm setting ends**

**Holidays** ➡  ➡  ➡ **From** 

● Editing entries ● Saving entry name ● Changing Alarm tone/video ● Setting handset to vibrate at Alarm Time ● Sounding Alarm tone even in Manner mode ● Activating Alarm based on World Clock time (P.9-38)

## At Alarm Time

Alarm activates; sounds/vibrates by related settings.



## Stopping Alarm

- Press a key.

## When Another Function is Active

- Alarm may not activate until handset returns to Standby.

## Incoming Calls

- Active Alarm stops for incoming calls. Information window opens after handset returns to Standby.

## When Snooze is Set

Alarm repeats at the set interval. Other Alarms do not activate while handset is Snoozing.

## Canceling Snooze

While Snoozing, ☐ ➔ Yes ➔ ☐

- Snooze is automatically canceled after a period of time.

## Canceling Alarm

1 In Alarm list, select entry ➔

2 Switch Off ➔ ☐

- Reactivate entry to use the same settings.

## Reactivating Entry

In , Switch On ➔ ☐

## Deleting Alarm

## One Entry

1 In Alarm list, select entry ➔

2 Reset Alarm ➔ ☐

3 Yes ➔ ☐

## All Entries

1 In Alarm list, select entry ➔

2 Clear All ➔ ☐

3 Enter Handset Code ➔ ☐  
➔ Yes ➔ ☐



# Using Wakeup TV

## Setting Wakeup TV

Follow these steps to activate TV at a specific time on a specific day of the week:

- Complete TV Area Setup beforehand.
- TV may not activate in poor signal conditions.

- 1 ➔ **Tools** ➔ ➔ In PIM/  
Lifestyle menu, **Wakeup TV**  
➔




Wakeup TV List

- 2 **--:--** ➔ ➔ **Enter hour**  
(24-hour format) ➔ **Enter**  
**minutes** ➔



Wakeup TV Menu

- 3 **Repeat:** ➔
- 4 **Selected Days** ➔



- 5 **Select day** ➔ (/✓) ➔  
**Complete selection** ➔
- 6 **Channel:** ➔
- 7 **Select channel** ➔
- 8 ➔ **Saved**  
• For more settings, repeat 2 - 5.
- 9 ➔ **Wakeup TV setting**  
**ends**

## Activating TV Once or Daily

- In 4, **Once or Every Day (All)** ➔   
➔ **From** 5

## Selecting/Canceling All Days

- In 5, ➔ **Check All or Uncheck All**  
➔

## Excluding Holidays

- In 5, select day ➔ (/✓) ➔  
**Complete selection** ➔ **Except**  
**Holidays** ➔ ➔ ➔ **From** 5

## Canceling Alarm

- Alarm activates at Wakeup TV time. To cancel Alarm, follow these steps:  
[Wakeup TV Menu] **Alarm On/Off:** ➔  
 ➔ **Off** ➔ ➔ **From** 5

## Adjusting Alarm Volume

- [Wakeup TV Menu] **Alarm Volume:** ➔  
 ➔ **Adjust level** ➔ ➔ **From** 5

## Advanced

- Editing entries Changing Alarm tone/video Sounding Alarm tone even in Manner mode (P.9-38)

## At Wakeup TV Time

TV activates after Alarm.



### Stopping Alarm Instantly

- While Alarm sounds/vibrates, press a key.
- When Another Function is Active**
- TV may not activate depending on the function.

### After TV is On for a Period of Time

- Confirmation appears. Choose **Yes** and press ☐ to exit TV.

## Canceling Wakeup TV

**1** In Wakeup TV list, select entry ➔ ☐

**2** **Wakeup TV Off** ➔ ☐

- Reactivate entry to use the same settings.

### Reactivating Entry

In **2**, **Wakeup TV On** ➔ ☐

## Deleting Wakeup TV

### One Entry

**1** In Wakeup TV list, select entry ➔ ☐

**2** **Reset Alarm** ➔ ☐

**3** **Yes** ➔ ☐

### All Entries

**1** In Wakeup TV list, select entry ➔ ☐

**2** **Clear All** ➔ ☐

**3** **Enter Handset Code** ➔ ☐  
➔ **Yes** ➔ ☐

## Playing Animation with Music & Illumination

Play preset animations or downloaded Flash® files with music and illumination. Set playback time, volume and illumination pattern as needed.

**1** ➔ **Tools** ➔ ➔ In PIM/Lifestyle menu, **Relaxation Time** ➔

**2** **Select type** ➔

- Animation appears.
- For **Flash®**, select a file and press .
  - Key LEDs do not illuminate for soundless Flash® files.

### Setting Relaxation Time

Follow these steps to set playback time, volume and Key Illumination pattern:

**1** ➔ **Tools** ➔ ➔ In PIM/Lifestyle menu, **Relaxation Time** ➔

**2** **Settings** ➔



**3** **Playback Time** ➔

**4** **Select time** ➔

- For custom playback time, select **Other**.

**5** **Volume** ➔

**6** **Adjust level** ➔

**7** **Set Key Illumi** ➔



**8** **Key Pattern** ➔

**9** **Select pattern** ➔ ➔

**10** ➔ **Standby returns**

### Disabling Key Illumination

In , **Set Key Illumi** ➔ ➔ **Switch On/Off** ➔ ➔ **Off** ➔ ➔

## Using Calculator

- 1 ➔ **Tools** ➔ ➔ In PIM/  
Lifestyle menu, **Calculator**  
➔



Calculator Window

- 2 Use Keypad to enter digits  
➔ **Calculate**
- 3 ➔ **Calculator ends**

### Key Assignments

<b>+</b> (Add)	
<b>-</b> (Subtract)	
<b>×</b> (Multiply)	
<b>÷</b> (Divide)	
<b>=</b> (Sum)	
<b>C-CE</b> (Clear)	
<b>CM</b> (Clear Memory)	
<b>RM</b> (Recall Memory)	
<b>M+</b> (Add to Memory)	
<b>.</b> (Decimal)	
<b>+/-</b> (Positive/Negative Value)	
<b>%</b> (Percentage)	

### Memory Calculation

- Clear Memory before starting new Memory calculations.
- Numbers saved in Memory remain until handset is powered off.

### Incoming Calls

- Calculations are not affected. End the call to return to Calculator.

### Using % Function

Use to find definite percentage of a known value.

Example: Calculate 30% of 800,000

Enter **800,000** ➔ **x** ➔ **30** ➔ **%**

■ **240,000** appears.


### Advanced

- Copying calculation results Changing exchange rate for currency conversion Converting currencies (**P.9-38**)


## Adding Expenses

### Entering Expenses

- 1 Enter amount ➔



- 2




- 3 Select Category ➔ ➔ Saved

#### Saving under Custom Category

In , *Other* ➔ ➔ Enter name ➔

### Checking Entries

- 1 ➔ *Tools* ➔ ➔ In PIM/  
Lifestyle menu, *Expenses*  
*Memo* ➔



- 2 *Totals* ➔



Expenses Memo List

- 3 ➔ Standby returns

#### Saving Entries to Notepad

[Expenses Memo List] ➔ *Save to*  
*Notepad* ➔

- All expense details are saved as a single entry.

### Deleting Entries

#### ■ One Entry

- 1 In Expenses Memo list, select entry ➔

- 2 *Delete Item* ➔

- 3 *Yes* ➔

#### ■ All Entries

- 1 In Expenses Memo list,

- 2 *Delete All* ➔

- 3 Enter Handset Code ➔   
➔ *Yes* ➔

### Advanced

- Changing Category of saved entry Changing amount Renaming Categories (P.9-39)

## Osaifu-Keitai® (Japanese)

Osaifu-Keitai® describes IC Card-equipped handsets that support e-money or credit functions/services. Osaifu-Keitai® encompasses a range of IC Card-based services on FeliCa-compatible SoftBank handsets. 936SH supports Osaifu-Keitai®. To use e-money, e-ticketing and reward points, etc., hold handset over a compatible reader/writer at shops, restaurants, and other retail outlets, etc.

### Basics

Before using Osaifu-Keitai®, activate Lifestyle-Appli, complete registration, customize settings and charge accounts.

#### Starting Lifestyle-Appli

- ➡ **Tools** ➡ ● ➡ In PIM/Lifestyle menu, **Osaifu-Keitai** ➡ ● ➡ **Lifestyle-Appli** ➡ ● ➡ Select application ➡ ●

#### Lifestyle-Appli Precautions

- Contact Osaifu-Keitai® service providers for Lifestyle-Appli registration and usage details.
- Keep service passwords/customer service contact information, etc. in a separate place.


### Using Osaifu-Keitai®

Follow these steps to conduct a transaction:

Example: Making an electronic payment

- Lifestyle-Appli activation is not necessary.
- Transactions are possible even when handset power is off (if battery is adequately charged).
- Calls/Internet transmissions do not affect transactions.

- 1 Place  logo over reader/writer ➡ Confirm scan results



Place this part  
over reader/writer

- Align handset parallel to reader/writer.

### Important Osaifu-Keitai® Usage Note

- SoftBank Mobile is not liable for damages resulting from accidental loss/alteration of IC Card data/settings.

#### When Placed Over Sensor

- If recognition is slow, move handset around slightly.
- Handset may respond automatically for some services.

### Advanced


-  ● Enabling to view e-money balances ● Moving applications up/down Balance Info list ● Removing applications from Balance Info list (P.9-39)

# Locking IC Card


## IC Card Lock

Restrict access to/prevent unauthorized use of Osaifu-Keitai® on handset.

- 1 ● ➔ **Tools** ➔ ● ➔ **In PIM/Lifestyle menu, Osaifu-Keitai**  
➔ ●



- 2 **IC Card Settings** ➔ ●



IC Card Settings Menu

- 3 **IC Card Lock** ➔ ● ➔ **On**  
➔ ●

- 4 **Enter Handset Code** ➔ ●  
➔ **Yes** ➔ ●

### Canceling IC Card Lock

- In ●, **IC Card Lock** ➔ ● ➔ **Off** ➔ ●  
➔ **Enter Handset Code** ➔ ●

## Advanced

- Customizing handset response to reader/writer commands ● Opening IC Card properties ● Changing IC Card Lock notice recipient ● Changing required Missed Call count for Call Remote Lock ● Restoring default Osaifu-Keitai® settings (**P.9-39**)

## Remote Lock

Disable Osaifu-Keitai® remotely by mail or phone.

<b>Mail Remote Lock</b>	Send mail to activate Remote Lock
<b>Call Remote Lock</b>	Call from a specified phone to activate Remote Lock


## Mail Remote Lock

## ■ Preparation on Handset

**1** ● ➔ **Tools** ➔ ● ➔ In PIM/Lifestyle menu, *Osaifu-Keitai* ➔ ●

**2** **IC Card Settings** ➔ ●

**3** **Remote Lock** ➔ ● ➔ Enter Handset Code ➔ ●



**4** **Mail Remote Lock** ➔ ●



Mail Remote Lock Menu

**5** **Remote Lock PW** ➔ ●

**6** Enter password ➔ ●

**7** **Switch On/Off** ➔ ●

**8** **On** ➔ ● ➔ ●

## Canceling Mail Remote Lock

In **5**, **Switch On/Off** ➔ ● ➔ **Off** ➔ ● ➔ ●

## ■ Activating Remote Lock via Mail

If handset cannot receive mail IC Card Lock is not set.

**1** Send S! Mail or e-mail to handset with password as subject

- After handset receives message, IC Card Lock is set and notice is sent as a reply.




## Call Remote Lock

### ■ Preparation on Handset


- 1 ➔ **Tools** ➔ ➔ In PIM/  
Lifestyle menu, **Osaifu-Keitai**  
➔

- 2 **IC Card Settings** ➔

- 3 **Remote Lock** ➔ ➔ Enter  
Handset Code ➔




- 4 **Call Remote Lock** ➔



Call Remote Lock Menu

- 5 **Phone No. to Lck 1 or  
Phone No. to Lck 2** ➔



- 6 **Phone Book** ➔ ➔ Select  
entry ➔ ➔ Select phone  
number ➔   
• Select **Phone Number** to enter directly.

- 7 **Switch On/Off** ➔

- 8 **On** ➔ ➔

Enabling Activation via Public Phone  
In , **Set Public Phone** ➔ ➔ **On**  
➔ ➔ **From**

Canceling Call Remote Lock  
In , **Switch On/Off** ➔ ➔ **Off** ➔

■ **Activating Remote Lock via Phone**  
If handset cannot receive calls IC Card  
Lock is not set.

- 1 **Using one of the specified  
phones, call handset**

- Send Caller ID.

- 2 **Handset receives call ➔  
End the call**

- The call is recorded as a Missed Call.

- 3 **Within three minutes, repeat  
1 - 2 twice**



- After the third Missed Call, IC Card  
Lock is set; a message announces  
Remote Lock activation. Confirm the  
message and end the call.

### If Series is Interrupted by Another Call

- Missed Call count is reset. Start over  
from the beginning.


## Faking Incoming Calls

Handset rings to emulate an incoming call.

- Save name and phone number to show as Caller ID.
- Ringer may be muted by handset settings. To override Silent setting, see **P.9-40**.

### Setting Simulated Call


- 1 ➔ **Tools** ➔ ➔ **In PIM/Lifestyle menu, *Simulated Call*** ➔



Simulated Call Menu

- 2 **Switch On/Off** ➔ ➔ **On** ➔

- 3 **Set Caller** ➔



- 4 **Name:** ➔ ➔ **Enter name** ➔

- 5 **Phone Number:** ➔ ➔ **Enter phone number** ➔ ➔

- 6 **Assign Tone** ➔ ➔ **Select tone/file** ➔

- 7 ➔ **PIM/Lifestyle menu returns**

#### When Name and Phone Number are Unset

- Handset rings with Caller ID "Withheld."

#### Canceling Simulated Call

[Simulated Call Menu] **Switch On/Off**

➔ ➔ **Off** ➔ ➔

#### Setting Wait Time

[Simulated Call Menu] **Receive Timing**

➔ ➔ **Select time** ➔ ➔

### Using Simulated Call

Available with handset open.

- 1 **(Long)**

- Handset rings and incoming Voice Call window opens.
- Ringtone stops after a period of time.

- 2 **In incoming Voice Call window, press**

- Voice Call window opens. (Softkeys are dummies.)

- 3 ➔ **Simulated Call ends**

#### When Receive Timing is Not *Immediately*

- Press or during wait time to cancel Simulated Call activation.
- Simulated Call activation is canceled by incoming calls, Alarms, etc. during wait time.

### Advanced

- Starting via Simulated Call menu • Clearing caller information • Overriding Silent volume setting (**P.9-40**)

## Using Stopwatch

Stopwatch stops when battery runs low.

- 1 ● ➔ **Tools** ➔ ● ➔ ●  
**Clocks/Gauges** ➔ **Stopwatch**  
 ➔ ●



Stopwatch Window

- 2 ● ➔ **Stopwatch starts**
- 3 ● ➔ **Stopwatch stops**  
 • Press ● to resume.
- 4 ☎ ➔ **Yes** ➔ ● ➔ **Stopwatch ends**  
 • Records are deleted when Stopwatch ends.

### Recording Lap Times

While Stopwatch is running, ⌘

### Saving Records to Notepad

After ⌘, ⌘ ➔ **Save to Notepad** ➔ ●

### Resetting Records


After ⌘, ⌘ ➔ **From** 2

### Incoming Calls

- Stopwatch is not affected by incoming calls. End the call to return.

## Using Countdown Timer

- 1** ➔ **Tools** ➔ ➔ **Clocks/Gauges** ➔ **Countdown Timer** ➔



Timer Entry Window

- 2** **Enter minutes** ➔ **Enter seconds** ➔



Countdown Timer Window

- Press to change time.

- 3** ➔ **Countdown starts**  
 • Press to stop/resume countdown.

- 4** **Set time elapses** ➔ **Tone sounds**

- 5** ➔ **Yes** ➔ ➔ **Countdown Timer ends**

### Using Timer Records

After **1**, ➔ **Select record** ➔ ➔

➔ **From** **3**

### Resetting Countdown Timer

Stop countdown and

### Incoming Calls

- Countdown is not affected by incoming calls. End the call to return.

### When Set Time Elapses

Tone sounds.



### Stopping Tone Instantly


- Press or a Side Key. (Tone stops automatically after a period of time.)

### When Timer Time Elapsed during a Call

- Tone sounds after the call.

## Opening World Clock


- 1 ➔ **Tools** ➔ ➔ ➔ **Clocks/Gauges** ➔ **World Clock** ➔



Local Time  
Zone

World Time  
Zone

- 2



Set Time Zone Window

- 3 ➔ **Select area** ➔

- 4 ➔ **World Clock ends**

**Advancing One Hour (Daylight Saving)**

[Set Time Zone Window]

■ To cancel, press .

**Adding Custom Time Zone**

[Set Time Zone Window] ➔ Enter


city name ➔ ➔ + or - ➔ ➔

Enter time difference ➔

### Opening World Clock in Standby

- 1 ➔ **Settings** ➔ ➔ In Phone menu, **Display** ➔

- 2 **Standby Display** ➔



- 3 **Clock/Calendar** ➔

- 4 **World Clock (L), etc.** ➔

- 5 ➔ **Standby returns**

## Using Hour Minder

### Setting Hour Minder

Follow these steps to activate the hourly time signal at selected hours:


- 1 → **Tools** → → **Clocks/Gauges** → **Hour Minder** →



Hour Minder Menu

- 2 **Switch On/Off** → → **On** →

- 3 **Select Time** →



- 4 **Select hour** → ( / ) → **Complete selection** →

- 5 → **Saved**

- 6 → **Hour Minder setting ends**

#### Adjusting Hour Minder Volume

In 2, **Advanced** → → **Volume:** → → **Adjust level** → → → **From** 5

#### Changing Hour Minder Duration

In 2, **Advanced** → → **Duration:** → → **Select time** → → → **From** 5

■ For custom Duration, select **Other**.

#### Selecting/Canceling All Hours

In 4, → **Check All** or **Uncheck All** →

### At Hour Minder Time

Hour Minder activates; sounds/vibrates by related settings.



#### Stopping Tone Instantly

- Press a key.

#### When Another Function is Active

- Hour Minder does not activate.

#### Incoming Calls

- Active Hour Minder stops for incoming calls.

### Canceling Hour Minder

- 1 In Hour Minder menu, **Switch On/Off** → → **Off** → →

### Advanced

- Changing Hour Minder tone/video ● Setting handset to vibrate at Hour Minder Time ● Sounding Hour Minder tone even in Manner mode ● Activating Hour Minder based on World Clock time (P.9-40)

# Using Pedometer

## Getting Started

- Count based on a pace of approximately 100 steps per minute over even terrain.
- Accuracy may be affected by course, terrain, walking style, etc.
- Avoid holding the handset; use a body worn case or a strap, or place handset inside a pocket or bag.
  - Avoid sudden/erratic movements.
- Steps are not counted in the following cases:
  - While handset is off
  - For the first few steps
  - While handset vibrates
- Handset use may affect accuracy.
- Use Pedometer only as a rough guide.


## Adjusting Counter Sensitivity

- ⬇ ➔ **Tools** ➔ ⬇ ➔ ⬇ ➔ **Clocks/Gauges** ➔ **Pedometer** ➔ ⬇ ➔ **Settings** ➔ ⬇ ➔ **Step Sensitivity** ➔ ⬇ ➔ **Select option** ➔ ⬇
- Select **Low** when steps seem overcounted; select **High** when they seem undercounted.

## Saving Body Information

Weight and pace entry required to view full Pedometer data.

- 1 ⬇ ➔ **Tools** ➔ ⬇ ➔ ⬇ ➔ **Clocks/Gauges** ➔ **Pedometer** ➔ ⬇



Pedometer Menu

- 2 **Settings** ➔ ⬇ ➔ **Body Info.** ➔ ⬇
- 3 **Enter Handset Code** ➔ ⬇



Body Info Menu

- 4 **Height** ➔ ⬇ ➔ **Enter height** ➔ ⬇
- 5 **Weight** ➔ ⬇ ➔ **Enter weight** ➔ ⬇
- 6 **Pace** ➔ ⬇ ➔ **Yes or No** ➔ ⬇
  - Choose **Yes** to enter pace automatically based on height.
- 7 **Enter pace** ➔ ⬇ ➔ ⬇

## Editing Body Information

- [Body Info Menu] **Select item** ➔ ⬇ ➔ **Enter value** ➔ ⬇ ➔ ⬇
- For **Pace**, automatic calculation confirmation appears (when height is entered).

## Activating Pedometer

- 1 In Pedometer menu, **Switch On/Off** ➔ ⬇
- 2 **On** ➔ ⬇

## Canceling Pedometer

- In 2, **Off** ➔ ⬇

## Pedometer Indicator

When Pedometer is active, today's step count appears in Standby.



## Viewing Step Count Records

1 In Pedometer menu, **Today's Walking** ➔ ●

2 ●



Steps Window

- Press (⏮) to toggle daily/weekly view.
- Press (⏮) to open previous day/week, or (⏭) to open next day/week.

3 Select time/date ➔ ●  
• Hourly/daily step counts appear.

4 (📞) ➔ Standby returns

### Resetting Today's Step Count

In (📞), (⏮) ➔ **Reset Day's Data** ➔ ●  
➔ **Yes** ➔ ●

### Resetting Log

[Steps Window] (⏮) ➔ **Walk Data**  
**Reset** ➔ ● ➔ **Enter Handset Code**  
➔ ● ➔ **Yes** ➔ ●

- Today's data is also reset.

## Setting Targets

Information window opens, etc. when target is achieved for these items:

Steps	Walking Time
Exercise	Calories
Distance	Fat burned

1 In Pedometer menu, **Settings** ➔ ● ➔ **Target** ➔ ●

2 **Target Settings** ➔ ●

3 Select item ➔ ● ➔ **Enter value/time** ➔ ●

- Other target settings may consequently change.

### Editing Targets

[Pedometer Menu] **Settings** ➔ ● ➔ **Target** ➔ ● ➔ **Target Settings** ➔ ●  
➔ **Select item** ➔ (⏮) ➔ **Enter value/time** ➔ ●

### When Target is Achieved

- A tone sounds and Information window opens. (Select **Goal Achievement** and press ● to open Pedometer Calendar.) Follow these steps to mute achievement tone:

[Pedometer Menu] **Settings** ➔ ● ➔ **Target** ➔ ● ➔ **Goal Announce** ➔ ● ➔ **Off** ➔ ●

### About Exercise (Ex)

- Ex and MET indicate amount and intensity of physical activity, respectively. Ex for walking is calculated by multiplying 3 METs by walking duration (hour).

## Advanced

1

- Changing Pedometer indicator ● Using Pedometer Calendar ● Checking accumulated data ● Resetting accumulated data ● Customizing achievement notice (P.9-40 - 9-41)



# Opening PC Documents

Supported File Formats:

PDF (.pdf)


Microsoft® Excel® (.xls)

Microsoft® Word (.doc)

Microsoft® PowerPoint® (.ppt)

- Some files may not appear correctly.
- Download files via the Internet.
- When transferring files from PCs, save to corresponding Memory Card folder (P.15-24).

**1** ➔ *Tools* ➔ ➔ *Doc./Rec.* ➔ *Document Viewer* ➔



**2** *Select file* ➔

**Zooming In/Out with Loupe (Magnifier)**  
In open file, (Long) ➔ Specify portion ➔ ➔ *Zoom Out* or *Zoom In* ➔


## Key Assignments

View Whole Page	
Scroll	
View Upper Left	
Toggle Full Screen View On/Off	
View Upper Right	
Zoom Out	
Continuous Zoom Out	(Long)
View Center	
Zoom In	
Continuous Zoom In	(Long)
View Lower Left	
Jump to Page	
View Lower Right	
Open Help	
Next Page	
Previous Page	
Fit Width	
Rotate 90 Degrees	

## Saving Text

### New Notepad Entry

- 1 ➔ **Tools** ➔ ➔ ➔ **Doc./Rec.** ➔ **Notepad** ➔



Notepad List

- 2 **<Add New Entry>** ➔



- 3 Enter text ➔
- 4 Select Category ➔ ➔ ➔ **Saved**

### Sorting Entries Temporarily

[Notepad List]


- Press to toggle sort options (Modified, Created, Category and Accessed).

### Inserting Notepad Text during Text Entry

- [Text Entry Window] ➔ **Notepad** ➔ ➔ **Call Notepad** ➔ ➔ ➔ **Select entry** ➔

### Opening Notepad

- 1 In Notepad list, select entry ➔



- 2 ➔ **LIST** ➔ **returns**

### Deleting Entries

#### ■ One Entry

- 1 In Notepad list, select entry ➔

- 2 **Delete Item** ➔ ➔ **Yes** ➔

#### ■ Selected Entries

- 1 In Notepad list, select entry ➔ ➔ **Setting/Manage** ➔

- 2 **Multiple Selection** ➔ ➔ ➔ **Select entry** ➔ (☐/☑) ➔ **Complete selection** ➔

- 3 **Delete** ➔ ➔ **Yes** ➔

### Unchecking All

- In , **Uncheck All** ➔

#### ■ All Entries

- 1 In Notepad list, select entry ➔ ➔ **Setting/Manage** ➔

- 2 **Delete All** ➔ ➔ **Enter Handset Code** ➔ ➔ **Yes** ➔

### Advanced

- Editing Notepad
- Searching text within all entries
- Inserting Notepad text into message text
- Sending entries via S! Mail
- Creating text files
- Importing text files
- Checking memory status
- Opening properties (P.9-41)

# Using ASCII Art

## Inserting ASCII Art




- 1 In message text entry window,  ➔ **Call ASCII Art**  
➔ 







- 2 Select entry ➔ 



## Previewing ASCII Art



- In , select entry ➔   
■ Press  to insert ASCII Art.

## Editing Entries

- 1  ➔ **Tools** ➔  ➔   
**Doc./Rec.** ➔ **ASCII Art** ➔ 



ASCII Art List

- 2 Select entry ➔  ➔ **Edit**  
➔ 




## Opening Entries

In , select entry ➔  ➔ **View** ➔ 

## Adding New Entries

In , **<Empty>** ➔  ➔ **Create ASCII Art** ➔ 

## Deleting Entries

- 1 In ASCII Art list, select entry  
➔  ➔ **Delete** ➔ 
- 2 **Yes** ➔ 


## Recording/Playing Voice

### Recording

- Recording stops if battery runs low while recording.
- Record conversations during calls via **Record Caller Voice**.

1 → **Tools** → → →


**Doc./Rec. → Voice Recorder**



Recording Window

2 → **Recording starts**

3 → **Recording stops**



- For **Extended Voice**, recording is saved automatically.

4 **Save** →

**Play Before Saving**  
 In 4, **Playback** → → **Playback starts** → → **Playback stops**  
**Starting Over**  
 In 4, → **From 2**

### Playback

1 In recording window, → **Ring Songs-Tones** →



2 **Select file** →

**Playing Files via Data Folder**  
 → **Data Folder** → → **Ring Songs-Tones** → → **Select file** →

### Playback Operations

Adjust Volume	
Pause/Resume	
Stop	

### Advanced

- Saving longer recordings
- Sending Voice files via S! Mail
- Switching storage media (P.9-41 - 9-42)

## 9-29

## Creating QR Codes

Create QR Codes from these items on handset:


Phone Book	My Details
Text Input	Ring Songs-Tones
Pictures	Notepad

Large items are divided into multiple QR Codes.

### Procedure


Follow these steps to create QR Codes from Data Folder files:

- 1 → **Tools** → → **Doc./Rec.** → **Barcode/Scan** →



- 2 **Create QR Code** →

- 3 **Data Folder** →



- 4 **Select folder** → → **Select file or entry** →

- QR Code is created.

- 5

- QR Code is saved to Data Folder (Pictures).

### From Phone Book Entries

In , **Phone Book** → → **Select entry** → →

### From My Details

In , **My Details** → → →

### From Entered Text

In , **Text Input** → → **Enter text** → →

### Switching Storage Media

In , → **Save to** → → **Phone or Memory Card** → →

### Attaching to S! Mail

In , → **Send As Message** → → **Complete message** →

### Incoming Calls


- QR Code creation is not affected by incoming calls. End the call to return.

## Scanning Business Cards

Scan business cards and save names, addresses, etc. to Phone Book.

- English business cards may not be scanned correctly.
- Some cards may not be scanned.

- 1** ● ➔ **Tools** ➔ ● ➔ ● ➔ **Doc./Rec.** ➔ **Barcode/Scan** ➔ ●



- 2** **Scan Card** ➔ ●


- 3** **Frame card on Display**



Scan Window

- 4** ●
- Press ● to stop scan.

- 5** ● ➔ **Scan results appear**



- 6** ● ➔ ●
- New Phone Book entry is saved.

### If Text Exceeds Phone Book Entry Item Character Limit

- Confirmation appears. Follow these steps to delete overage:

**Yes** ➔ ●

### Switching Storage Media

After ●, ● ➔ **Save to** ➔ ● ➔ ●

**Select storage media** ➔ ● ➔ ●

### Saving Scanned Image as Phone Book Picture

After ●, ● ➔ **Add Image** ➔ ● ➔ ●

**On** ➔ ● ➔ ●

### Starting Over

After ●, ● ➔ **Yes** ➔ ● ➔ **From** ●

### Key Assignments in Scan Window

Toggle Focus Mode	3
Switch to Photo Camera	7
Focus Lock	8
Mobile Light On/Off	11
Adjust Brightness	12
Open Help	0

### Advanced

- Saving to Notepad ● Pasting to message text ● Copying text (P.9-44)

## Scanning Text


Scan text and save it to Notepad, etc.

Available Modes:

Full	Capture text in full screen and scan a selected line
Line	Capture a few lines of text and scan a selected line

- To toggle mode, press in scan window.
- Some text cannot be scanned.


**1**  $\Rightarrow$  **Tools**  $\Rightarrow$   $\Rightarrow$   $\Rightarrow$



**2** **Scan Text**  $\Rightarrow$

- To change mode, press in scan window.

**3** **Frame text in center of Display**




Scan Window

**4**  $\Rightarrow$  **Scan starts**

- Press to stop scan.

**5** **Select line**  $\Rightarrow$   $\Rightarrow$  **Scan results appear**

**6**



**7**  $\Rightarrow$  **Notepad**  $\Rightarrow$

**Correcting Text Type**

After ,  $\Rightarrow$  **Change Mode**  $\Rightarrow$

$\Rightarrow$  **Select type**  $\Rightarrow$   $\Rightarrow$  **From**

**Editing Scanned Text**

After ,  $\Rightarrow$  **Select/Edit**  $\Rightarrow$   $\Rightarrow$

**Select character**  $\Rightarrow$  **Select alternative from list or edit directly**  $\Rightarrow$  **From**

**Starting Over**

In ,  $\Rightarrow$  **Yes**  $\Rightarrow$   $\Rightarrow$  **From**

**Key Assignments in Scan Window**

Toggle Focus Mode	
Switch to Photo Camera	
Focus Lock	
Mobile Light On/Off	
Adjust Brightness	
Open Help	

### Advanced

- Scanning and pasting during text entry
- Scanning more text
- Saving scan results
- Saving linked info to Phone Book
- Opening saved scan results
- Using linked info
- Pasting to message text
- Copying text (P.9-44 - 9-45)




# Using Kanji Grabber

Scan a word of up to ten kanji and look it up in dictionaries.


Some text cannot be scanned.

- 1 ● ➔ **Tools** ➔ ● ➔ ●  
**Doc./Rec.** ➔ **Barcode/Scan**  
 ➔ ●



- 2 **Kanji Grabber** ➔ ●

- 3 **Frame kanji in Loupe**



- 4 ●  
 • Scan results (kanji) appear.

- 5 ●

- 6 **Select dictionary** ➔ ● ➔  
**Search** ➔ ●

- 7 **Select word, etc.** ➔ ●  
 • Definition/translation window opens.

## Starting Over

In ⑤, ⑥ ➔ From ③

## Key Assignments in Scan Window

Toggle 2x Magnification On/Off	③
Toggle Focus Mode	⑦
Switch to Photo Camera	⑦
Focus Lock	⑧
Mobile Light On/Off	⑨
Adjust Brightness	⑩
Open Help	⑪

## Advanced

- Scanning and pasting during text entry (P.9-45)

## Calendar

### View Settings

Changing default view	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calendar</i> ➔ ● ➔ ☰ ➔ <i>Calendar Settings</i> ➔ ● ➔ <i>Default View</i> ➔ ● ➔ Select type ➔ ●</p>
Jumping to specified date	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calendar</i> ➔ ● ➔ 8 ➔ Enter date ➔ ●</p>
Changing date color	<p><b>Start Here</b> ● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calendar</i> ➔ ● ➔ See below</p> <p><b>By Days of the Week</b></p> <p>☰ ➔ <i>Calendar Settings</i> ➔ ● ➔ <i>Set Color</i> ➔ ● ➔ <i>By Week</i> ➔ ● ➔ Select day ➔ ● ➔ Select color ➔ ●</p>
	<p><b>By Date</b></p> <p>Select date ➔ 4 ➔ Select color ➔ ●</p> <p>• Not available in 6Month View.</p>
	<p><b>Resetting "By Date" Colors</b></p> <p>☰ ➔ <i>Calendar Settings</i> ➔ ● ➔ <i>Set Color</i> ➔ ● ➔ <i>Reset Color</i> ➔ ● ➔ Select option ➔ ● ➔ Yes ➔ ●</p>
Selecting task view option	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calendar</i> ➔ ● ➔ ☰ ➔ <i>Calendar Settings</i> ➔ ● ➔ <i>Tasks View</i> ➔ ● ➔ Select option ➔ ●</p>
Adding stamps (Month/3Month View)	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calendar</i> ➔ ● ➔ Select date ➔ 2 ➔ Select stamp ➔ ●</p>
Hiding schedules	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calendar</i> ➔ ● ➔ Select date ➔ ● ➔ Select entry ➔ ● ➔ <i>Secret:</i> ➔ ● ➔ <i>On</i> ➔ ● ➔ ☰</p>

### Saving additional holidays

**Start Here** ● ➔ *Tools* ➔ ● ➔ In PIM/Lifestyle menu, *Calendar* ➔ ● ➔ ☰ ➔ *Calendar Settings* ➔ ● ➔ *Set Holiday* ➔ ● ➔ ☰ ➔ *Private* ➔ See below

#### Adding Holidays

<Empty> ➔ ● ➔ Enter name ➔ ● ➔ Enter date ➔ ● ➔ Select frequency ➔ ● ➔ ☰

#### Editing Added Holidays

Select holiday ➔ ☰ ➔ *Edit* ➔ ● ➔ *Name:* ➔ ● ➔ Enter name ➔ ● ➔ *Date:* ➔ ● ➔ Enter date ➔ ● ➔ Select frequency ➔ ● ➔ ☰

### Removing/restoring holidays

● ➔ *Tools* ➔ ● ➔ In PIM/Lifestyle menu, *Calendar* ➔ ● ➔ ☰ ➔ *Calendar Settings* ➔ ● ➔ *Set Holiday* ➔ ● ➔ ☰ ➔ *Private or Public* ➔ Select holiday ➔ ● (☐/☑)

## ■ Saving/Editing Schedules

Setting Category/ Location	<p><b>Start Here</b> ● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔ Select date ● ➔ ● ➔ Select entry ● ➔ ● ➔ See below</p> <p><b>Category</b> <b>Category:</b> ● ➔ ● ➔ Select Category ● ➔ ● ➔ </p> <p><b>Location</b> <b>Location:</b> ● ➔ ● ➔ Enter location ● ➔ ● ➔ </p>
Creating Categories	<p><b>Start Here</b> ● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔  ➔ <b>Calendar Settings</b> ● ➔ ● ➔ <b>Set Category</b> ● ➔ See below</p> <p><b>Renaming Categories</b> Select Category ● ➔ ● ➔ <b>Edit Category Name</b> ● ➔ ● ➔ Enter name ● ➔ ●</p> <p><b>Changing Icons</b> Select Category ● ➔ ● ➔ <b>Change Icon</b> ● ➔ ● ➔ Select Pictogram ● ➔ ●</p> <p><b>Resetting</b>  ➔ <b>Reset Settings</b> ● ➔ ● ➔ Enter Handset Code ● ➔ ● ➔ <b>Yes</b> ● ➔ ●</p>
Saving repetitive schedules	<p>● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔ Select date ● ➔ ● ➔ Select entry ● ➔ ● ➔ <b>Repeat:</b> ● ➔ ● ➔ Select frequency ● ➔ ● ➔ Enter repeat time ● ➔ ● ➔ </p> <p>● Repeat time is not available for <i>Every Year</i>.</p>

Saving S! Friend's Status information	<p><b>Start Here</b> ● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔ Select date ● ➔ ● ➔ Select entry ● ➔ ● ➔ ● ➔ <b>S! Friend's Status:</b> ● ➔ ● ➔ <b>Link Setting:</b> ● ➔ ● ➔ <b>Linked</b> ● ➔ ● ➔ See below</p> <p><b>Availability</b> <b>Answer Status:</b> ● ➔ ● ➔ <b>Edit</b> ● ➔  ➔  ➔ </p> <p>● Set Category first.</p> <p><b>Comment</b> <b>Comment:</b> ● ➔ ● ➔ Enter text ● ➔ ● ➔  ➔ </p> <p>● Set Category first.</p>
Editing entries	<p>● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔ Select date ● ➔ ● ➔ Select entry ● ➔ ● ➔ Select item ● ➔ ● ➔ <b>Edit</b> in the same manner as saving schedules ● ➔ </p>
Changing Alarm tone/video & duration	<p><b>Start Here</b> ● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔ Select date ● ➔ ● ➔ Select entry ● ➔ ● ➔ ● ➔ <b>Alarm:</b> ● ➔ ● ➔ See below</p> <p><b>Alarm Tone/Video</b> <b>Assign Tone/Video:</b> ● ➔ ● ➔ Select folder ● ➔ ● ➔ Select tone/file ● ➔ ● ➔  ➔ </p> <p>● Select start point if required.</p> <p><b>Duration</b> <b>Duration:</b> ● ➔ ● ➔ Select time ● ➔ ● ➔  ➔ </p>
Changing Alarm volume	<p>● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔  ➔ <b>Alarm Settings</b> ● ➔ ● ➔ <b>Alarm Volume:</b> ● ➔ ● ➔ Adjust level ● ➔ ●</p>
Selecting Vibration option	<p>● ➔ <b>Tools</b> ● ➔ ● ➔ In PIM/Lifestyle menu, <b>Calendar</b> ● ➔ ● ➔  ➔ <b>Alarm Settings</b> ● ➔ ● ➔ <b>Vibration:</b> ● ➔ ● ➔ Select option ● ➔ ●</p>

Sounding Alarm tone even in Manner mode	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → ☐ → <i>Alarm Settings</i> → ●</p> <p>→ <i>For Manner Mode:</i> → ● → <i>Ring</i> → ● → <i>Yes</i> → ●</p>
---	--

## ■ Managing Schedules

Searching entries	<p>[Start Here] ● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → See below</p> <p><b>By Part of Subject</b></p> <p>6 → Enter text → ●</p> <p><b>By Category</b></p> <p>9 → Select Category → ●</p>
Checking memory status	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → Select date → ☐ → <i>Memory Status</i> → ●</p>
Deleting all entries	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → ☐ → <i>Delete</i> → ● → <i>All Appointments</i> → ● → Enter Handset Code → ● → <i>Yes</i> → ●</p>
Deleting entries by specifying week (Week View)	<p>[Start Here] ● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → See below</p> <p><b>Within One Week</b></p> <p>Select date → ☐ → <i>Delete</i> → ● → <i>All This Week</i> → ● → <i>Yes</i> → ●</p> <p><b>Up to the End of Previous Week</b></p> <p>Select date → ☐ → <i>Delete</i> → ● → <i>Up to Last Week</i> → ● → <i>Yes</i> → ●</p>

Deleting entries by specifying month (Month/3Month View)	<p>[Start Here] ● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → See below</p> <p><b>Within One Month</b></p> <p>Select date → ☐ → <i>Delete</i> → ● → <i>All This Month</i> → ● → <i>Yes</i> → ●</p> <p><b>Up to the End of Previous Month</b></p> <p>Select date → ☐ → <i>Delete</i> → ● → <i>Up to Last Month</i> → ● → <i>Yes</i> → ●</p>
Deleting entries in six months (6Month View)	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Calendar</i> → ● → ☐ → <i>Delete</i> → ● → <i>All This 6Months</i> → ● → <i>Yes</i> → ●</p>

## Tasks

### ■ Task List

Hiding tasks	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Tasks</i> → ● → Select task → ☐ → <i>Edit</i> → ●</p> <p>→ <i>Secret:</i> → ● → <i>On</i> → ● → ☐</p>
--------------	---

### ■ Saving/Editing Tasks

Editing tasks	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Tasks</i> → ● → Select task → ☐ → <i>Edit</i> → ●</p> <p>→ Select item → ● → Edit in the same manner as saving tasks → ☐</p>
Setting priority	<p>● → <i>Tools</i> → ● → In PIM/Lifestyle menu, <i>Tasks</i> → ● → Select task → ☐ → <i>Edit</i> → ●</p> <p>→ <i>Priority:</i> → ● → Select priority → ● → ☐</p>

Changing Alarm tone/ video & duration	<p><b>Start Here</b> → <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → Select task → <b>Edit</b> → <b>Alarm:</b> → See below</p> <p><b>Alarm Tone/Video</b>  <b>Assign Tone/Video:</b> → Select folder → Select tone/file →          • Select start point if required.</p> <p><b>Duration</b>  <b>Duration:</b> → Select time →</p>
Changing Alarm volume	<p>→ <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Alarm Settings</b> → <b>Alarm Volume:</b> → Adjust level →</p>
Selecting Vibration option	<p>→ <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Alarm Settings</b> → <b>Vibration:</b> → Select option →</p>
Sounding Alarm tone even in Manner mode	<p>→ <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Alarm Settings</b> → <b>For Manner Mode:</b> → Ring → Yes →</p>

## Managing Tasks

Searching tasks	<p><b>Start Here</b> → <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Find</b> → See below</p> <p><b>By Part of Subject</b>  <b>By Subject</b> → Enter text →</p> <p><b>By Due Date</b>  <b>By Due Date</b> → Enter date →</p>
Sorting tasks by priority	<p>→ <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Sort</b> → <b>Priority</b> →</p>
Checking memory status	<p>→ <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Memory Status</b> →</p>
Deleting all tasks	<p>→ <b>Tools</b> → In PIM/Lifestyle menu, <b>Tasks</b> → <b>Delete</b> → <b>All Tasks</b> → Enter Handset Code → Yes →</p>

## Alarms

Editing entries	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Alarms</i> ➔ ● ➔ Select entry ➔ ● ➔ Select item ➔ ● ➔ Edit in the same manner as saving entries ➔ Ⓜ</p>
Saving entry name	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Alarms</i> ➔ ● ➔ Select entry ➔ ● ➔ <i>Subject:</i> ➔ ● ➔ Enter name ➔ ● ➔ Ⓜ</p>
Changing Alarm tone/video	<p><i>(Start Here)</i> ● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Alarms</i> ➔ ● ➔ Select entry ➔ ● ➔ <i>Assign Tone/Video:</i> ➔ ● ➔ See below</p> <p><b>Using Preset Tone or Data Folder File</b> Select folder ➔ ● ➔ Select tone/file ➔ ● ➔ Ⓜ • Select start point if required.</p> <p><b>Using Customized Screen Tone/Video</b> <i>Customized Screen</i> ➔ ● ➔ Ⓜ</p>
Setting handset to vibrate at Alarm Time	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Alarms</i> ➔ ● ➔ Select entry ➔ ● ➔ <i>Vibration:</i> ➔ ● ➔ <i>On or Link to Sound</i> ➔ ● ➔ Ⓜ • Select <i>Link to Sound</i> to allow compatible SMAF files to control vibration.</p>
Sounding Alarm tone even in Manner mode	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Alarms</i> ➔ ● ➔ <i>Settings</i> ➔ ● ➔ <i>For Manner Mode</i> ➔ ● ➔ <i>Ring</i> ➔ ● ➔ <i>Yes</i> ➔ ●</p>
Activating Alarm based on World Clock time	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Alarms</i> ➔ ● ➔ <i>Settings</i> ➔ ● ➔ <i>Link to World Clk</i> ➔ ● ➔ <i>On</i> ➔ ●</p>

## Wakeup TV

Editing entries	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Wakeup TV</i> ➔ ● ➔ Select entry ➔ ● ➔ Select item ➔ ● ➔ Edit in the same manner as saving entries ➔ Ⓜ</p>
Changing Alarm tone/video	<p><i>(Start Here)</i> ● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Wakeup TV</i> ➔ ● ➔ Select entry ➔ ● ➔ <i>Assign Tone/Video:</i> ➔ ● ➔ See below</p> <p><b>Using Preset Tone or Data Folder File</b> Select folder ➔ ● ➔ Select tone/file ➔ ● ➔ Ⓜ • Select start point if required.</p> <p><b>Using Customized Screen Tone/Video</b> <i>Customized Screen</i> ➔ ● ➔ Ⓜ</p>
Sounding Alarm tone even in Manner mode	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Wakeup TV</i> ➔ ● ➔ <i>For Manner Mode</i> ➔ ● ➔ <i>Ring</i> ➔ ● ➔ <i>Yes</i> ➔ ●</p>

## Calculator

Copying calculation results	While result appears, ⊞ ➔ <i>Copy</i> ➔ ●
Changing exchange rate for currency conversion	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calculator</i> ➔ ● ➔ ⊞ ➔ <i>Money Converter</i> ➔ ● ➔ <i>Exchange Rate</i> ➔ ● ➔ <i>Domestic or Foreign</i> ➔ ● ➔ Enter rate ➔ ●</p>
Converting currencies	<p>● ➔ <i>Tools</i> ➔ ● ➔ In PIM/Lifestyle menu, <i>Calculator</i> ➔ ● ➔ Enter amount of money ➔ ⊞ ➔ <i>Money Converter</i> ➔ ● ➔ <i>To Domestic or To Foreign</i> ➔ ● • Set Exchange Rate first.</p>

Expenses Memo	
Changing Category of saved entry	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Expenses Memo</i></li> <li>Totals</li> <li>Select entry</li> <li>Select Category</li> </ul>
Changing amount	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Expenses Memo</i></li> <li>Totals</li> <li>Select entry</li> <li>Change Amount</li> <li>Edit</li> </ul>
Renaming Categories	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Expenses Memo</i></li> <li>Edit Category</li> <li>Select Category</li> <li>Enter name</li> </ul>

### Osaifu-Keitai®

Enabling to view e-money balances	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Balance Info</li> <li>Enter Handset Code</li> <li>&lt;Empty&gt;</li> <li>S! Appli or Lifestyle-Appli</li> <li>Select application</li> <li>For use with compatible Lifestyle-Applications.</li> <li>Start Lifestyle-Appli once before adding it to Balance Info list.</li> </ul>
Moving applications up/down Balance Info list	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Balance Info</li> <li>Enter Handset Code</li> <li>Select application</li> <li>Move</li> <li>Select target location</li> </ul>
Removing applications from Balance Info list	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Balance Info</li> <li>Enter Handset Code</li> <li>Select application</li> <li>Delete</li> </ul>

Customizing handset response to reader/writer commands	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Interface Settings</li> <li>Enter Handset Code</li> <li>Select item</li> <li>Off</li> </ul>
Opening IC Card properties	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>IC Card Status</li> </ul>
Changing IC Card Lock notice recipient	<p>Start Here</p> <ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Remote Lock</li> <li>Enter Handset Code</li> <li>Mail Remote Lock</li> <li>Notice Settings</li> <li>Send Notice</li> <li>See below</li> </ul> <p><b>Changing Recipient</b></p> <ul style="list-style-type: none"> <li>To Set Recipient</li> <li>Set Recipient</li> <li>Select method</li> <li>Select/enter number/address</li> <li>Yr</li> <li>Omit step of pressing <b>BACK</b> when selecting <i>Phone Book</i> as setting method.</li> </ul> <p><b>Disabling Notice</b></p> <ul style="list-style-type: none"> <li>Off</li> <li>Yr</li> </ul>
Changing required Missed Call count for Call Remote Lock	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Remote Lock</li> <li>Enter Handset Code</li> <li>Call Remote Lock</li> <li>Count for Lock</li> <li>Enter Missed Call count</li> <li>Yr</li> </ul>
Restoring default Osaifu-Keitai® settings	<ul style="list-style-type: none"> <li>Tools</li> <li>In PIM/Lifestyle menu, <i>Osaifu-Keitai</i></li> <li>IC Card Settings</li> <li>Set to Default</li> <li>Enter Handset Code</li> <li>Yes</li> </ul>

## Simulated Call

Starting via Simulated Call menu	<p>● → <b>Tools</b> → ● → In PIM/Lifestyle menu, <b>Simulated Call</b> → ● → <b>Receive Simulated Call</b> → ● → <b>Yes</b> → ●</p> <ul style="list-style-type: none"> <li>Simulated Call starts immediately regardless of Receive Timing setting.</li> <li>Settings remain even after starting Simulated Call during setup.</li> </ul>
Clearing caller information	<p>● → <b>Tools</b> → ● → In PIM/Lifestyle menu, <b>Simulated Call</b> → ● → <b>Set Caller</b> → ● → [Menu] → <b>Yes</b> → ● → [Yes] → [Yes]</p>
Overriding Silent volume setting	<p>● → <b>Tools</b> → ● → In PIM/Lifestyle menu, <b>Simulated Call</b> → ● → <b>For Silent Mode</b> → ● → <b>Ring</b> → ● → <b>Yes</b> → ● → [Yes] → [Yes]</p>

## Hour Minder

Changing Hour Minder tone/video	<p>● → <b>Tools</b> → ● → [Clocks/Gauges] → <b>Hour Minder</b> → ● → <b>Advanced</b> → ● → <b>Assign Tone/Video:</b> → ● → <b>Select folder</b> → ● → <b>Select tone/file</b> → ● → [Yes] → [Yes]</p> <ul style="list-style-type: none"> <li>Select start point if required.</li> </ul>
Setting handset to vibrate at Hour Minder Time	<p>● → <b>Tools</b> → ● → [Clocks/Gauges] → <b>Hour Minder</b> → ● → <b>Advanced</b> → ● → <b>Vibration:</b> → ● → <b>On or Link to Sound</b> → ● → [Yes] → [Yes]</p> <ul style="list-style-type: none"> <li>Select <b>Link to Sound</b> to allow compatible SMAF files to control vibration.</li> </ul>

Sounding Hour Minder tone even in Manner mode

● → **Tools** → ● → [Clocks/Gauges] → **Hour Minder** → ● → **Advanced** → ● → **For Manner Mode:** → ● → **Ring** → ● → **Yes** → ● → [Yes] → [Yes]

Activating Hour Minder based on World Clock time

● → **Tools** → ● → [Clocks/Gauges] → **Hour Minder** → ● → **Advanced** → ● → **Link to World Clk:** → ● → **On** → ● → [Yes] → [Yes]

## Pedometer

Changing Pedometer indicator	<p>● → <b>Settings</b> → ● → In Phone menu, <b>Display</b> → ● → <b>Standby Display</b> → ● → <b>Pedometer</b> → ● → <b>Select item</b> → ●</p>
Using Pedometer Calendar	<p>● → <b>Tools</b> → ● → [Clocks/Gauges] → <b>Pedometer</b> → ● → <b>Pedometer Calendar</b> → ● → <b>Select date</b> → ●</p> <ul style="list-style-type: none"> <li>Degree of achievement appears.</li> <li>Press [X] or [H] to view previous or next month.</li> </ul>
Checking accumulated data	<p>● → <b>Tools</b> → ● → [Clocks/Gauges] → <b>Pedometer</b> → ● → <b>Accumulated Data</b> → ●</p> <ul style="list-style-type: none"> <li>Change in body information is reflected in the data.</li> </ul>
Resetting accumulated data	<p>● → <b>Tools</b> → ● → [Clocks/Gauges] → <b>Pedometer</b> → ● → <b>Accumulated Data</b> → ● → [Menu] → <b>Reset Walk Data</b> → ● → <b>Enter Handset Code</b> → ● → <b>Yes</b> → ●</p> <ul style="list-style-type: none"> <li>Averages are also reset.</li> </ul>



Customizing achievement notice	<b>Start Here</b> → Tools → Clocks/Gauges → Pedometer → Settings → Target → Goal Announce → On See below
	<b>Changing Tone</b> Goal Sound → Select pattern
	<b>Changing Tone Volume</b> Goal Volume → Adjust level
	<b>Selecting Vibration Option</b> Vibration → Select option
	<b>Changing Duration</b> Duration → Select time • For custom Duration, select <b>Other</b> and press .

## Notepad

Editing Notepad	<b>Start Here</b> → Tools → Doc./Rec. → Notepad → Select entry → See below
	<b>Editing Text</b> Edit Text → Edit
	<b>Changing Category</b> Change Category → Select Category
Searching text within all entries	Tools → Doc./Rec. → Notepad → Select entry → Search → Enter text
Inserting Notepad text into message text	Tools → Doc./Rec. → Notepad → Select entry → Send → As Message Text → S! Mail or SMS → Complete message • S! Mail Composition window opens automatically depending on character count.

Sending entries via S! Mail	Tools → Doc./Rec. → Notepad → Select entry → Send → Via Message → Complete message
Creating text files	Tools → Doc./Rec. → Notepad → Select entry → Setting/Manage → Create Text File → Enter name → Save here
Importing text files	Tools → Doc./Rec. → Notepad → Select entry → Setting/Manage → Import Text File → Select file
Checking memory status	Tools → Doc./Rec. → Notepad → Select entry → Setting/Manage → Memory Status
Opening properties	Tools → Doc./Rec. → Notepad → Select entry → Details

## Voice Recorder

Saving longer recordings	Tools → Doc./Rec. → Voice Recorder → Record Time → Extended Voice → Recording starts → Recording ends • Insert Memory Card to record in <b>Extended Voice</b> mode. (Recording is saved automatically.)
Sending Voice files via S! Mail	Tools → Doc./Rec. → Voice Recorder → Recording starts → Recording ends → Save and Send → Complete message • Available in <b>For Message</b> mode.

## Switching storage media

- Tools → Doc./Rec. → Voice Recorder → Save Recording to → Select option
- Available in **For Message** mode.
- Set to **Ask Each Time** to select media after every recording.

## Scan Barcode

## Scanning during text entry

**Start Here** In a text entry window, Scan → Scan Code → Frame barcode in center of Display → See below

## Pasting All Scan Results



## Pasting a Part of Scan Results

Select first character → Highlight text range →

## Scanning continuously

- Tools → Doc./Rec. → Barcode/Scan → Scan Barcode → Continuous Scan → On → Frame barcode in center of Display
- Choose **Yes** to continue scanning or **No** and press to view scan results.

## Reading saved barcode images

Tools → Doc./Rec. → Barcode/Scan → Open Barcode → Select file

## Saving scan results

Tools → Doc./Rec. → Barcode/Scan → Scan Barcode → Frame barcode in center of Display → Save

## Saving to Notepad

Tools → Doc./Rec. → Barcode/Scan → Scan Barcode → Frame barcode in center of Display → Notepad

## Saving linked info to Phone Book

- Tools → Doc./Rec. → Barcode/Scan → Scan Barcode → Frame barcode in center of Display → Select number or mail address → Save to Ph.Book → As New Entry → Complete other fields
- To add to an existing entry, select **As New Detail**.
- When **MEMORY:** appears in scan results, press to enter the items underlined with a dotted line automatically in Phone Book entry window.

## Opening saved scan results

- Tools → Doc./Rec. → Barcode/Scan → Scanned Results → Select file
- Select a file and press to rename files, open properties or delete files.
- Some files may not open.

## Using linked info

**Start Here** Tools → Doc./Rec. → Barcode/Scan → Scan Barcode → Frame barcode in center of Display → See below

## Dialing Numbers

Select phone number →

## Sending Messages

Select mail address → Complete message

- When **MAILTO:** appears in scan results, press to enter the items underlined with a dotted line automatically in Composition window.

## Accessing Internet Sites

Select URL →

Using images as Wallpaper	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Barcode</b> ➔ ● ➔ <b>Frame barcode in center of Display</b> ➔ ● ➔ <b>Select image</b> ➔ ☐ ➔ <b>Set as Wallpaper</b> ➔ ● ➔ ●</p> <ul style="list-style-type: none"> <li>For images smaller or larger than Display, Wallpaper Display options appear; follow onscreen prompts.</li> </ul>
Saving images & melodies	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Barcode</b> ➔ ● ➔ <b>Frame barcode in center of Display</b> ➔ ● ➔ <b>Select file</b> ➔ ☐ ➔ <b>To Data Folder</b> ➔ ●</p>
Opening or playing files	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Barcode</b> ➔ ● ➔ <b>Frame barcode in center of Display</b> ➔ ● ➔ <b>Select file</b> ➔ ●</p>
Using images for System Graphics	<p>● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Barcode</b> ➔ ● ➔ <b>Frame barcode in center of Display</b> ➔ ● ➔ <b>Select image</b> ➔ ☐ ➔ <b>As System</b> ➔ ● ➔ <b>Select item</b> ➔ ● ➔ <b>Specify image area</b> ➔ ●</p> <ul style="list-style-type: none"> <li>Some images may be usable without specifying image area.</li> </ul>

Pasting to message text	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Barcode</b> ➔ ● ➔ <b>Frame barcode in center of Display</b> ➔ ● ➔ ☐ ➔ <b>Send Message</b> ➔ ● ➔ See below</p> <p><b>All Text</b></p> <p>● ➔ <b>S! Mail or SMS</b> ➔ ● ➔ <b>Complete message</b> ➔ ☑</p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul>
	<p><b>Selected Text</b></p> <p>☐ ➔ <b>Select first character</b> ➔ ● ➔ <b>Highlight text range</b> ➔ ● ➔ <b>S! Mail or SMS</b> ➔ ● ➔ <b>Complete message</b> ➔ ☑</p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul>
Copying text	<p><b>Start Here</b> ● ➔ <b>Tools</b> ➔ ● ➔ ⌂ <b>Doc./Rec.</b> ➔ <b>Barcode/Scan</b> ➔ ● ➔ <b>Scan Barcode</b> ➔ ● ➔ <b>Frame barcode in center of Display</b> ➔ ● ➔ <b>See below</b></p> <p><b>Text</b></p> <p>☐ ➔ <b>Copy</b> ➔ ● ➔ <b>Select first character</b> ➔ ● ➔ <b>Highlight text range</b> ➔ ●</p> <p><b>Number, Address or URL</b></p> <p>Select number, mail address or URL ➔ ☐ ➔ <b>Copy Telephone, Copy Address or Copy URL</b> ➔ ●</p>

## Scan Card

Saving to Notepad	<p>● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scan Card</i> → ● → Frame card in center of Display → ● → ● → ☹️ → <i>Notepad</i> → ●</p>
Pasting to message text	<p>[Start Here] ● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scan Card</i> → ● → Frame card in center of Display → ● → ● → ☹️ → <i>Send Message</i> → ● → See below</p> <p><b>All Text</b></p> <p>● → <i>S! Mail or SMS</i> → ● → Complete message → ☹️</p> <ul style="list-style-type: none"> <li>• S! Mail Composition window opens automatically depending on character count.</li> </ul> <p><b>Selected Text</b></p> <p>☹️ → Select first character → ● → Highlight text range → ● → <i>S! Mail or SMS</i> → ● → Complete message → ☹️</p> <ul style="list-style-type: none"> <li>• S! Mail Composition window opens automatically depending on character count.</li> </ul>
Copying text	<p>[Start Here] ● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scan Card</i> → ● → Frame card in center of Display → ● → ● → See below</p> <p><b>Text</b></p> <p>☹️ → <i>Copy</i> → ● → Select first character → ● → Highlight text range → ●</p>

## Scan Text

Scanning and pasting during text entry	<p>In a text entry window, ☹️ → <i>Scan</i> → ● → <i>Scan Text</i> → ● → Frame text in center of Display → ● → Select line → ● → ●</p>
Scanning more text	<p>● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scan Text</i> → ● → Frame text in center of Display → ● → Select line → ● → ● → ☹️ → <i>Continue Part</i> or <i>Scan More</i> → ●</p> <ul style="list-style-type: none"> <li>• Select <i>Continue Part</i> to enter additional text or <i>Scan More</i> to enter text after a line break.</li> </ul>
Saving scan results	<p>● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scan Text</i> → ● → Frame text in center of Display → ● → Select line → ● → ● → ☹️ → <i>Save</i> → ●</p>
Saving linked info to Phone Book	<p>● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scan Text</i> → ● → Frame text in center of Display → ● → Select line → ● → ● → Select number or mail address → ☹️ → <i>Save to Ph.Book</i> → ● → <i>As New Entry</i> → ● → Complete other fields → ☹️</p> <ul style="list-style-type: none"> <li>• To add to an existing entry, select <i>As New Detail</i>.</li> </ul>
Opening saved scan results	<p>● → <i>Tools</i> → ● → ☹️ <i>Doc./Rec.</i> → <i>Barcode/Scan</i> → ● → <i>Scanned Results</i> → ● → Select file → ●</p> <ul style="list-style-type: none"> <li>• Select a file and press ☹️ to rename files, open properties or delete files.</li> <li>• Some files may not open.</li> </ul>

Using linked info	<p>Start Here  → Tools  →  Doc./Rec. → Barcode/Scan  → Scan Text  → Frame text in center of Display  → Select line  → See below</p>
	<p><b>Dialing Numbers</b> Select phone number  → </p>
	<p><b>Sending Messages</b> Select mail address  → Complete message </p>
Pasting to message text	<p><b>Accessing Internet Sites</b> Select URL </p>
	<p>Start Here  → Tools  →  Doc./Rec. → Barcode/Scan  → Scan Text  → Frame text in center of Display  → Select line  →  Send Message  → See below</p>
	<p><b>All Text</b>  → S! Mail or SMS  → Complete message </p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul>
	<p><b>Selected Text</b>  → Select first character  → Highlight text range  → S! Mail or SMS  → Complete message </p> <ul style="list-style-type: none"> <li>S! Mail Composition window opens automatically depending on character count.</li> </ul>


Copying text	<p>Start Here  → Tools  →  Doc./Rec. → Barcode/Scan  → Scan Text  → Frame text in center of Display  → Select line  → See below</p>
	<p><b>Text</b>  → Copy  → Select first character  → Highlight text range </p>
	<p><b>Number, Address or URL</b> Select number, mail address or URL  → Copy Telephone, Copy Address or Copy URL </p>
<b>Kanji Grabber</b>	
Scanning and pasting during text entry	<p>In a text entry window,  → Scan  → Kanji Grabber  → Frame kanji in Loupe  → Scan results appear </p>

## Osaifu-Keitai®

### ? Cannot use Osaifu-Keitai® (S! FeliCa)

- Battery may be low. Charge battery or install a charged battery.

### ? Recognition via reader/writer takes time

- Check  logo area. Foreign articles can block/hamper recognition.

### ? Call Remote Lock does not activate even after specified number of Missed Calls

- Missed Call count is reset by calls from other numbers. If series is interrupted, start over from the beginning.
- When Call Forwarding is active, Missed Calls may not be recorded.

## Wakeup TV

### ? TV does not activate with specified channel

- If Wakeup TV Time arrives while TV is active, channel does not switch to the specified one.

## Voice Recorder

### ? Cannot record properly

- If incompatible microphone is connected, recording may fail.

### ? Noise/skipping occurs

- Avoid shocks to handset while recording; may cause noise or skipping.

### ? Recording takes time to start

- Recording window may take longer to open as more Voice files are saved on Memory Card.

## Scanning Barcode/Card/Text

### ? Cannot read barcodes properly

- Scan may fail if barcode is dirty or unclear.
- Scan may fail if barcode is scanned under inadequate light.
- Scan may fail if multiple barcodes are captured at one time.



### Cannot read barcodes during text entry

- Scanning is not available during calls or when mobile camera is active.



### Cannot read barcode images in Data Folder automatically

- When scan fails, follow onscreen instructions and select next barcode image manually.



### Cannot scan business cards properly

- Scan fails if business card is printed in light-colored text on a dark background, handwritten or printed in casual/decorative fonts, decorated with a background pattern, or designed with both vertical and horizontal text.
- Scan may fail if business card is printed in light-colored text on a light background, printed in italics or extremely small fonts, decorated with a logo or logo-like text, printed on a glossy paper or other material, or dirty/folded.



### Cannot scan text properly

- Scanning over 35 characters at one time may yield poor results.
- Adjust to frame text in [ ]. Letters at the ends may be distorted.